

600EF Software Update

Updating the software in your System 600EF Note Acceptor is as easy as one, two, three. “Flash” memory technology has replaced the EPROM “chip” technology used in the previous System 600FST Note Acceptors.



Follow the simple procedure below whenever you receive a “Flash” memory stick for updating the program in your System 600EF Note Acceptor.

Note: The System 600EF Note Acceptor can remain mounted in the changer and must be powered up. A small light (LED) above the memory stick socket will flash slowly during normal operation.

1. Remove the rear panel to gain access to the memory stick socket.
2. Insert the pre-programmed “Flash” memory stick into the socket.
3. Press the reset button on the Keypad or Data Terminal to initiate the program “download”.
4. Wait for the LED above the memory stick socket to return to the normal slow flash from the rapid flash that occurs during the program download.
5. Once the download is completed, remove the memory stick, reattach the rear panel and test machine for proper operation.

Note: When multiple copies of a program update are ordered on a single flash memory stick, this procedure can be repeated in multiple System 600EF Note Acceptors until all copies have been used. An unsuccessful update attempt will not decrease the number of copies remaining on the memory stick. Also, once a note acceptor has been updated, any further attempts to install the same update will not decrease the number of copies remaining on the memory stick. You can reduce your cost for future software updates by saving the memory stick, and returning it to a Standard Change-Makers service center for new updates when available.