

## **Series 2000 Bill Acceptor Questions?**

1. **What is the part number for the 9 pin to 12 pin 115 VAC Power Harness?**  
The part number is 250077006.

2. **What is the part number for the 9 pin to 12 pin 24 VAC Power Harness?**  
The part number is 250075007.

3. **What is the part number for the Series 2000 MDB Power Harness for 24 VAC units?**  
The part number is 250071009.

4. **What is the part number for the Locking Hasp Kit for the Series 2000?**  
The part number is 250066027 pack two.

5. **What is the part number for the Pulse Meter Kit for the Series 2000?**  
The part number is 250068009.

6. **What is the part number for the Compact Bezel Kit?**  
The part number is 250065014.

7. **What does 2 Flashes on a Series 2000 mean?**  
This means the Series 2000 Bill Acceptor is not externally enabled to pull in bills. Check the following: the coin tubes of the coin changer must be at least half full, check the dip switches for the bill acceptor and coin changer, check the harnesses, check the connectors for bent pins, check the door switch if applical.

8. **How often should the Series 2000 Bill Acceptors belts be replaced?**  
The belts should be replaced under the following conditions:

Belts should not be replaced before 250,000 cycles or three ( 3 ) years unless the belts are damaged ( cuts, tears or attacked by a foreign substance ) or show the following:

- Cracking or splitting on the working surface of the belt(s)
- Missing material such as large, deep pits
- Broken or exposed cords on the working surface of the belt(s)
- Severely frayed edges with several cords exposed or broken.